AUTOMOWER MAINTENANCE PROGRAM

	OK Che	Even Y	ear Grent?	rd Vear		
1		X	<u> </u>	Remove the body and clean the chassis.		
2		X		Check the rubber bellows on the cutting height adjustment. Replace if damaged.		
3		X		Check the rubber bellows on the rear joysticks. Replace if damaged.		
4		X		Check all rubber grommets into the chassis that they seal properly. Replace if damaged.		
5		X		Clean the ultrasonic sensors carefully, 450X/ 450XH/550/550H		
6		X		Check the ventilation filter and clean carefully with a soft brush.		
7		X		Check the tightening torque of screws on the chassis.		
8		X		Check the blades and blade screws. Replace if damaged.		
9		X		Clean the headlights carefully, (If applicable)		
10		X		Clean the charging station.		
11		X		Check and polish the charging strips on the product and the contact strips on the charging station		
12		X		Check the cable to the products charging plates. Replace if damaged.		
13		X		Check that docking and charging work correctly.		
14		X		Make a complete Auto test in Autocheck.		
15		X		Check that docking and charging work correctly		
16		X		Do a Battery test in Autocheck and check the battery con	dition.	
17		X		Charge the battery.		
18		X		Read the service bulletins for potential recommended upd	lates	
19			X	Replace the ventilation filter.		
20			X	Replace the rubber bellows on the front joysticks.		
21			X	Inspect and grease the front wheel bearing. Replace if damaged.		
22			X	Open the chassis and replace the chassis sealing strips.		
Α.	Annual	Mainte	nance	Program	\$100 + parts	
B. Annual Maintenance Program including Pick-up & Return				\$100 + parts		
	(Includes c		Delivery Fee extra (see below)			
C. Firmware Update (A la carte) \$49					\$49	
- Connector Protection Box \$10.99					•	
, ,					\$75	
- Wire Repair Kit \$35					\$35	

^{*} Pick up and delivery fee will be based upon location. For pricing please text or call 801-810-4779